



ANSMANN Desktop Charger with display DC5140PD 140W 3 Years Warranty*

Intelligent USB charger 140 W with GaN technology and LED power indicator for notebooks, smartphones, tablets and other USB devices.

Features

- USB charger with 5 USB ports and 140 W
- Display of the current power consumption
- Intelligent charge controller ensures optimum charging
- Multisafe technology protects both your end-device and the charger
- Suitable for devices that can be charged or operated via USB
- Input: 100 - 240V AC Wide-range input enables worldwide use
- Voltage range: 5 - 20V DC
- Power: 140 W



Power



Ultra fast charging



Output 2× USB & 3× USB Type-C (PD)



for notebooks & phones



Multisafe Technology



Gallium nitride technology



Power Delivery with PPS protocol



Quickcharge 3.0 compatible



Article number: 1001-0149
 Product content: Desktop Charger with display DC5140PD 140W, manual
 Customs tariff number: 85044083900
 Packing Unit: 42 Pieces (600 × 400 × 300 mm)



Specifications

Output voltage	5 - 20V DC			
Input voltage	100 - 240V AC			
Max. output current	5 A			
Max. input current	2.5 A			
Charging currents	Mode	Voltage	Current	Power
	USB-A1 A2	5,0 V	3,0 A	15,0 W
	USB-A1 A2	9,0 V	3,0 A	27,0 W
	USB-A1 A2	12,0 V	3,0 A	36,0 W
	USB-A1 A2	20,0 V	3,0 A	60,0 W
	USB-C1 C2 C3 PD	5,0 V	3,0 A	15,0 W
	USB-C1 C2 C3 PD	9,0 V	3,0 A	27,0 W
	USB-C1 C2 C3 PD	12,0 V	3,0 A	36,0 W
	USB-C1 C2 C3 PD	15,0 V	3,0 A	45,0 W
	USB-C1 C2 C3 PD	20,0 V	5,0 A	100,0 W
	USB-A1 + A2: A1	5,0 V	2,4 A	12,0 W
	USB-A1 + A2: A2	5,0 V	2,4 A	12,0 W
	USB-C1 + C2: C1	5,0 V	3,0 A	15,0 W
	USB-C1 + C2: C1	9,0 V	3,0 A	27,0 W
	USB-C1 + C2: C1	12,0 V	3,0 A	36,0 W
	USB-C1 + C2: C1	15,0 V	3,0 A	45,0 W
	USB-C1 + C2: C1	20,0 V	4,8 A	95,0 W

Mode	Voltage	Current	Power
USB-C1 + C2: C2	5,0 V	3,0 A	15,0 W
USB-C1 + C2: C2	9,0 V	3,0 A	27,0 W
USB-C1 + C2: C2	12,0 V	3,0 A	36,0 W
USB-C1 + C2: C2	15,0 V	3,0 A	45,0 W
USB-C1 + C2: C2	20,0 V	2,3 A	45,0 W
USB-C1 + C3: C1	5,0 V	3,0 A	15,0 W
USB-C1 + C3: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C3: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C3: C1	15,0 V	3,0 A	45,0 W
USB-C1 + C3: C1	20,0 V	4,8 A	95,0 W
USB-C1 + C3: C3	5,0 V	3,0 A	15,0 W
USB-C1 + C3: C3	9,0 V	3,0 A	27,0 W
USB-C1 + C3: C3	12,0 V	3,0 A	36,0 W
USB-C1 + C3: C3	15,0 V	3,0 A	45,0 W
USB-C1 + C3: C3	20,0 V	2,3 A	45,0 W
USB-C2 + C3: C2	5,0 V	3,0 A	15,0 W
USB-C2 + C3: C2	9,0 V	3,0 A	27,0 W
USB-C2 + C3: C2	12,0 V	3,0 A	36,0 W
USB-C2 + C3: C2	15,0 V	3,0 A	45,0 W
USB-C2 + C3: C2	20,0 V	4,8 A	95,0 W
USB-C2 + C3: C3	5,0 V	3,0 A	15,0 W
USB-C2 + C3: C3	9,0 V	3,0 A	27,0 W
USB-C2 + C3: C3	12,0 V	3,0 A	36,0 W
USB-C2 + C3: C3	15,0 V	3,0 A	45,0 W
USB-C2 + C3: C3	20,0 V	2,3 A	45,0 W
USB-C1 + C2 + C3: C1	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + C3: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + C3: C1	15,0 V	3,0 A	45,0 W
USB-C1 + C2 + C3: C1	20,0 V	3,3 A	65,0 W

Mode	Voltage	Current	Power
USB-C1 + C2 + C3: C2	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3: C2	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + C3: C2	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + C3: C2	15,0 V	3,0 A	45,0 W
USB-C1 + C2 + C3: C2	20,0 V	2,3 A	45,0 W
USB-C1 + C2 + C3: C3	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3: C3	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + C3: C3	12,0 V	2,5 A	30,0 W
USB-C1 + C2 + C3: C3	15,0 V	2,0 A	30,0 W
USB-C1 + C2 + C3: C3	20,0 V	1,5 A	30,0 W
USB-C1 + C2 + C3 + A1: C1	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3 + A1: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + C3 + A1: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + C3 + A1: C1	15,0 V	3,0 A	45,0 W
USB-C1 + C2 + C3 + A1: C1	20,0 V	3,3 A	65,0 W
USB-C1 + C2 + C3 + A1: C2	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3 + A1: C2	9,0 V	3,0 A	27,0 W

Mode	Voltage	Current	Power
USB-C1 + C2 + C3 + A1: C2	12,0 V	2,5 A	30,0 W
USB-C1 + C2 + C3 + A1: C2	15,0 V	2,0 A	30,0 W
USB-C1 + C2 + C3 + A1: C2	20,0 V	1,5 A	30,0 W
USB-C1 + C2 + C3 + A1: C3	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3 + A1: C3	9,0 V	2,2 A	20,0 W
USB-C1 + C2 + C3 + A1: C3	12,0 V	1,7 A	20,0 W
USB-C1 + C2 + C3 + A1: C3	15,0 V	1,3 A	20,0 W
USB-C1 + C2 + C3 + A1: A1	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3 + A1: A1	9,0 V	2,7 A	24,3 W
USB-C1 + C2 + C3 + A1: A1	12,0 V	2,0 A	24,0 W
USB-C1 + C2 + C3 + A1: A1	20,0 V	1,3 A	25,0 W
USB-C1 + C2 + C3 + A2: C1	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3 + A2: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + C3 + A2: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + C3 + A2: C1	15,0 V	3,0 A	45,0 W
USB-C1 + C2 + C3 + A2: C1	20,0 V	3,3 A	65,0 W
USB-C1 + C2 + C3 + A2: C2	5,0 V	3,0 A	15,0 W

Mode	Voltage	Current	Power
USB-C1 + C2 + C3 + A2: C2	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + C3 + A2: C2	12,0 V	2,5 A	30,0 W
USB-C1 + C2 + C3 + A2: C2	20,0 V	1,5 A	30,0 W
USB-C1 + C2 + C3 + A2: C3	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3 + A2: C3	9,0 V	2,2 A	20,0 W
USB-C1 + C2 + C3 + A2: C3	12,0 V	1,7 A	20,0 W
USB-C1 + C2 + C3 + A2: C3	15,0 V	1,3 A	20,0 W
USB-C1 + C2 + C3 + A2: A2	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3 + A2: A2	9,0 V	2,7 A	24,3 W
USB-C1 + C2 + C3 + A2: A2	12,0 V	2,0 A	24,0 W
USB-C1 + C2 + C3 + A2: A2	20,0 V	1,3 A	25,0 W
USB-C1 + C2 + C3 + A1 + A2: C1	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3 + A1 + A2: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + C3 + A1 + A2: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + C3 + A1 + A2: C1	15,0 V	3,0 A	45,0 W
USB-C1 + C2 + C3 + A1 + A2: C1	20,0 V	3,3 A	65,0 W
USB-C1 + C2 + C3 + A1 + A2: C2	5,0 V	3,0 A	15,0 W

Mode	Voltage	Current	Power
USB-C1 + C2 + C3 + A1 + A2: C2	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + C3 + A1 + A2: C2	12,0 V	2,5 A	30,0 W
USB-C1 + C2 + C3 + A1 + A2: C2	15,0 V	2,0 A	30,0 W
USB-C1 + C2 + C3 + A1 + A2: C2	20,0 V	1,5 A	30,0 W
USB-C1 + C2 + C3 + A1 + A2: C3	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + C3 + A1 + A2: C3	9,0 V	2,2 A	20,0 W
USB-C1 + C2 + C3 + A1 + A2: C3	12,0 V	1,7 A	20,0 W
USB-C1 + C2 + C3 + A1 + A2: C3	15,0 V	1,3 A	20,0 W
USB-C1 + C2 + C3 + A1 + A2: A1	5,0 V	2,4 A	12,0 W
USB-C1 + C2 + C3 + A1 + A2: A2	5,0 V	2,4 A	12,0 W
USB-C1 + A1: C1	5,0 V	3,0 A	15,0 W
USB-C1 + A1: C1	9,0 V	3,0 A	27,0 W
USB-C1 + A1: C1	12,0 V	3,0 A	36,0 W
USB-C1 + A1: C1	15,0 V	3,0 A	45,0 W
USB-C1 + A1: C1	20,0 V	5,0 A	100,0 W
USB-C1 + A1: A1	5,0 V	3,0 A	15,0 W
USB-C1 + A1: A1	9,0 V	3,0 A	27,0 W
USB-C1 + A1: A1	12,0 V	3,0 A	36,0 W
USB-C1 + A1: A1	20,0 V	1,8 A	36,0 W
USB-C1 + A2: C1	5,0 V	3,0 A	15,0 W
USB-C1 + A2: C1	9,0 V	3,0 A	27,0 W
USB-C1 + A2: C1	12,0 V	3,0 A	36,0 W
USB-C1 + A2: C1	15,0 V	3,0 A	45,0 W
USB-C1 + A2: C1	20,0 V	5,0 A	100,0 W
USB-C1 + A2: A2	5,0 V	3,0 A	15,0 W

Mode	Voltage	Current	Power
USB-C1 + A2: A2	9,0 V	3,0 A	27,0 W
USB-C1 + A2: A2	12,0 V	3,0 A	36,0 W
USB-C1 + A2: A2	20,0 V	1,8 A	36,0 W
USB-C2 + A1: C2	5,0 V	3,0 A	15,0 W
USB-C2 + A1: C2	9,0 V	3,0 A	27,0 W
USB-C2 + A1: C2	12,0 V	3,0 A	36,0 W
USB-C2 + A1: C2	15,0 V	3,0 A	45,0 W
USB-C2 + A1: C2	20,0 V	5,0 A	100,0 W
USB-C2 + A1: A1	5,0 V	3,0 A	15,0 W
USB-C2 + A1: A1	9,0 V	3,0 A	27,0 W
USB-C2 + A1: A1	12,0 V	3,0 A	36,0 W
USB-C2 + A1: A1	20,0 V	1,8 A	36,0 W
USB-C2 + A2: C2	5,0 V	3,0 A	15,0 W
USB-C2 + A2: C2	9,0 V	3,0 A	27,0 W
USB-C2 + A2: C2	12,0 V	3,0 A	36,0 W
USB-C2 + A2: C2	15,0 V	3,0 A	45,0 W
USB-C2 + A2: C2	20,0 V	5,0 A	100,0 W
USB-C2 + A2: A2	5,0 V	3,0 A	15,0 W
USB-C2 + A2: A2	9,0 V	3,0 A	27,0 W
USB-C2 + A2: A2	12,0 V	3,0 A	36,0 W
USB-C2 + A2: A2	20,0 V	1,8 A	36,0 W
USB-C3 + A1: C3	5,0 V	3,0 A	15,0 W
USB-C3 + A1: C3	9,0 V	3,0 A	27,0 W
USB-C3 + A1: C3	12,0 V	3,0 A	36,0 W
USB-C3 + A1: C3	15,0 V	3,0 A	45,0 W
USB-C3 + A1: C3	20,0 V	5,0 A	100,0 W
USB-C3 + A1: A1	5,0 V	3,0 A	15,0 W
USB-C3 + A1: A1	9,0 V	3,0 A	27,0 W
USB-C3 + A1: A1	12,0 V	3,0 A	36,0 W
USB-C3 + A1: A1	20,0 V	1,8 A	36,0 W
USB-C3 + A2: C3	5,0 V	3,0 A	15,0 W
USB-C3 + A2: C3	9,0 V	3,0 A	27,0 W
USB-C3 + A2: C3	12,0 V	3,0 A	36,0 W
USB-C3 + A2: C3	15,0 V	3,0 A	45,0 W
USB-C3 + A2: C3	20,0 V	5,0 A	100,0 W

Mode	Voltage	Current	Power
USB-C3 + A2: A2	5,0 V	3,0 A	15,0 W
USB-C3 + A2: A2	9,0 V	3,0 A	27,0 W
USB-C3 + A2: A2	12,0 V	3,0 A	36,0 W
USB-C3 + A2: A2	20,0 V	1,8 A	36,0 W
USB-C1 + C2 + A1: C1	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + A1: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + A1: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + A1: C1	15,0 V	3,0 A	45,0 W
USB-C1 + C2 + A1: C1	20,0 V	3,3 A	65,0 W
USB-C1 + C2 + A1: C2	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + A1: C2	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + A1: C2	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + A1: C2	15,0 V	3,0 A	45,0 W
USB-C1 + C2 + A1: C2	20,0 V	2,3 A	45,0 W
USB-C1 + C2 + A1: A1	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + A1: A1	9,0 V	2,7 A	24,3 W
USB-C1 + C2 + A1: A1	12,0 V	2,0 A	24,0 W
USB-C1 + C2 + A1: A1	20,0 V	1,3 A	25,0 W
USB-C1 + C3 + A1: C1	5,0 V	3,0 A	15,0 W

Mode	Voltage	Current	Power
USB-C1 + C3 + A1: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C3 + A1: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C3 + A1: C1	15,0 V	3,0 A	45,0 W
USB-C1 + C3 + A1: C1	20,0 V	3,3 A	65,0 W
USB-C1 + C3 + A1: C3	5,0 V	3,0 A	15,0 W
USB-C1 + C3 + A1: C3	9,0 V	3,0 A	27,0 W
USB-C1 + C3 + A1: C3	12,0 V	3,0 A	36,0 W
USB-C1 + C3 + A1: C3	15,0 V	3,0 A	45,0 W
USB-C1 + C3 + A1: C3	20,0 V	2,3 A	45,0 W
USB-C1 + C3 + A1: A1	5,0 V	3,0 A	15,0 W
USB-C1 + C3 + A1: A1	9,0 V	2,7 A	24,3 W
USB-C1 + C3 + A1: A1	12,0 V	2,0 A	24,0 W
USB-C1 + C3 + A1: A1	20,0 V	1,3 A	25,0 W
USB-C1 + C2 + A2: C1	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + A2: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + A2: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + A2: C1	15,0 V	3,0 A	45,0 W

Mode	Voltage	Current	Power
USB-C1 + C2 + A2: C1	20,0 V	3,3 A	65,0 W
USB-C1 + C2 + A2: C2	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + A2: C2	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + A2: C2	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + A2: C2	15,0 V	3,0 A	45,0 W
USB-C1 + C2 + A2: C2	20,0 V	2,3 A	45,0 W
USB-C1 + C2 + A2: A2	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + A2: A2	9,0 V	2,7 A	24,3 W
USB-C1 + C2 + A2: A2	12,0 V	2,0 A	24,0 W
USB-C1 + C2 + A2: A2	20,0 V	1,3 A	25,0 W
USB-C1 + C3 + A2: C1	5,0 V	3,0 A	15,0 W
USB-C1 + C3 + A2: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C3 + A2: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C3 + A2: C1	15,0 V	3,0 A	45,0 W
USB-C1 + C3 + A2: C1	20,0 V	3,3 A	65,0 W
USB-C1 + C3 + A2: C3	5,0 V	3,0 A	15,0 W
USB-C1 + C3 + A2: C3	9,0 V	3,0 A	27,0 W

Mode	Voltage	Current	Power
USB-C1 + C3 + A2: C3	12,0 V	3,0 A	36,0 W
USB-C1 + C3 + A2: C3	15,0 V	3,0 A	45,0 W
USB-C1 + C3 + A2: C3	20,0 V	2,3 A	45,0 W
USB-C1 + C3 + A2: A2	5,0 V	3,0 A	15,0 W
USB-C1 + C3 + A2: A2	9,0 V	2,7 A	24,3 W
USB-C1 + C3 + A2: A2	12,0 V	2,0 A	24,0 W
USB-C1 + C3 + A2: A2	20,0 V	1,3 A	25,0 W
USB-C2 + C3 + A1: C2	5,0 V	3,0 A	15,0 W
USB-C2 + C3 + A1: C2	9,0 V	3,0 A	27,0 W
USB-C2 + C3 + A1: C2	12,0 V	3,0 A	36,0 W
USB-C2 + C3 + A1: C2	15,0 V	3,0 A	45,0 W
USB-C2 + C3 + A1: C2	20,0 V	3,3 A	65,0 W
USB-C2 + C3 + A1: C3	5,0 V	3,0 A	15,0 W
USB-C2 + C3 + A1: C3	9,0 V	3,0 A	27,0 W
USB-C2 + C3 + A1: C3	12,0 V	3,0 A	36,0 W
USB-C2 + C3 + A1: C3	15,0 V	3,0 A	45,0 W
USB-C2 + C3 + A1: C3	20,0 V	2,3 A	45,0 W

Mode	Voltage	Current	Power
USB-C2 + C3 + A1: A1	5,0 V	3,0 A	15,0 W
USB-C2 + C3 + A1: A1	9,0 V	2,7 A	24,3 W
USB-C2 + C3 + A1: A1	12,0 V	2,0 A	24,0 W
USB-C2 + C3 + A1: A1	20,0 V	1,3 A	25,0 W
USB-C2 + C3 + A2: C2	5,0 V	3,0 A	15,0 W
USB-C2 + C3 + A2: C2	9,0 V	3,0 A	27,0 W
USB-C2 + C3 + A2: C2	12,0 V	3,0 A	36,0 W
USB-C2 + C3 + A2: C2	15,0 V	3,0 A	45,0 W
USB-C2 + C3 + A2: C2	20,0 V	3,3 A	65,0 W
USB-C2 + C3 + A2: C3	5,0 V	3,0 A	15,0 W
USB-C2 + C3 + A2: C3	9,0 V	3,0 A	27,0 W
USB-C2 + C3 + A2: C3	12,0 V	3,0 A	36,0 W
USB-C2 + C3 + A2: C3	15,0 V	3,0 A	45,0 W
USB-C2 + C3 + A2: C3	20,0 V	2,3 A	45,0 W
USB-C2 + C3 + A2: A2	5,0 V	3,0 A	15,0 W
USB-C2 + C3 + A2: A2	9,0 V	2,7 A	24,3 W
USB-C2 + C3 + A2: A2	12,0 V	2,0 A	24,0 W

Mode	Voltage	Current	Power
USB-C2 + C3 + A2: A2	20,0 V	1,3 A	25,0 W
USB-C1 + C2 + A1 + A2: C1	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + A1 + A2: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + A1 + A2: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + A1 + A2: C1	15,0 V	3,0 A	45,0 W
USB-C1 + C2 + A1 + A2: C1	20,0 V	3,3 A	65,0 W
USB-C1 + C2 + A1 + A2: C2	5,0 V	3,0 A	15,0 W
USB-C1 + C2 + A1 + A2: C2	9,0 V	3,0 A	27,0 W
USB-C1 + C2 + A1 + A2: C2	12,0 V	3,0 A	36,0 W
USB-C1 + C2 + A1 + A2: C2	15,0 V	3,0 A	45,0 W
USB-C1 + C2 + A1 + A2: C2	20,0 V	2,3 A	45,0 W
USB-C1 + C2 + A1 + A2: A1	5,0 V	2,4 A	12,0 W
USB-C1 + C2 + A1 + A2: A2	5,0 V	2,4 A	12,0 W
USB-C1 + C3 + A1 + A2: C1	5,0 V	3,0 A	15,0 W
USB-C1 + C3 + A1 + A2: C1	9,0 V	3,0 A	27,0 W
USB-C1 + C3 + A1 + A2: C1	12,0 V	3,0 A	36,0 W
USB-C1 + C3 + A1 + A2: C1	15,0 V	3,0 A	45,0 W

Mode	Voltage	Current	Power
USB-C1 + C3 + A1 + A2: C1	20,0 V	3,3 A	65,0 W
USB-C1 + C3 + A1 + A2: C3	5,0 V	3,0 A	15,0 W
USB-C1 + C3 + A1 + A2: C3	9,0 V	3,0 A	27,0 W
USB-C1 + C3 + A1 + A2: C3	12,0 V	3,0 A	36,0 W
USB-C1 + C3 + A1 + A2: C3	15,0 V	3,0 A	45,0 W
USB-C1 + C3 + A1 + A2: C3	20,0 V	2,3 A	45,0 W
USB-C1 + C3 + A1 + A2: A1	5,0 V	2,4 A	12,0 W
USB-C1 + C3 + A1 + A2: A2	5,0 V	2,4 A	12,0 W
USB-C2 + C3 + A1 + A2: C2	5,0 V	3,0 A	15,0 W
USB-C2 + C3 + A1 + A2: C2	9,0 V	3,0 A	27,0 W
USB-C2 + C3 + A1 + A2: C2	12,0 V	3,0 A	36,0 W
USB-C2 + C3 + A1 + A2: C2	15,0 V	3,0 A	45,0 W
USB-C2 + C3 + A1 + A2: C2	20,0 V	2,3 A	65,0 W
USB-C2 + C3 + A1 + A2: C3	5,0 V	3,0 A	15,0 W
USB-C2 + C3 + A1 + A2: C3	9,0 V	3,0 A	27,0 W
USB-C2 + C3 + A1 + A2: C3	12,0 V	3,0 A	36,0 W
USB-C2 + C3 + A1 + A2: C3	15,0 V	3,0 A	45,0 W

Mode	Voltage	Current	Power
USB-C2 + C3 + A1 + A2: C3	20,0 V	2,3 A	45,0 W
USB-C2 + C3 + A1 + A2: A1	5,0 V	2,4 A	12,0 W
USB-C2 + C3 + A1 + A2: A2	5,0 V	2,4 A	12,0 W
USB-C1 + A1 + A2: C1	5,0 V	3,0 A	15,0 W
USB-C1 + A1 + A2: C1	9,0 V	3,0 A	27,0 W
USB-C1 + A1 + A2: C1	12,0 V	3,0 A	36,0 W
USB-C1 + A1 + A2: C1	15,0 V	3,0 A	45,0 W
USB-C1 + A1 + A2: C1	20,0 V	5,0 A	100,0 W
USB-C1 + A1 + A2: A1	5,0 V	2,4 A	12,0 W
USB-C1 + A1 + A2: A2	5,0 V	2,4 A	12,0 W
USB-C2 + A1 + A2: C2	5,0 V	3,0 A	15,0 W
USB-C2 + A1 + A2: C2	9,0 V	3,0 A	27,0 W
USB-C2 + A1 + A2: C2	12,0 V	3,0 A	36,0 W
USB-C2 + A1 + A2: C2	15,0 V	3,0 A	45,0 W
USB-C2 + A1 + A2: C2	20,0 V	5,0 A	100,0 W
USB-C2 + A1 + A2: A1	5,0 V	2,4 A	12,0 W
USB-C2 + A1 + A2: A2	5,0 V	2,4 A	12,0 W

	Mode	Voltage	Current	Power
	USB-C3 + A1 + A2: C3	5,0 V	3,0 A	15,0 W
	USB-C3 + A1 + A2: C3	9,0 V	3,0 A	27,0 W
	USB-C3 + A1 + A2: C3	12,0 V	3,0 A	36,0 W
	USB-C3 + A1 + A2: C3	15,0 V	3,0 A	45,0 W
	USB-C3 + A1 + A2: C3	20,0 V	5,0 A	100,0 W
	USB-C3 + A1 + A2: A1	5,0 V	2,4 A	12,0 W
	USB-C3 + A1 + A2: A2	5,0 V	2,4 A	12,0 W
	USB-C1 + C2 + C3 + A2: C2	15,0 V	2,0 A	30,0 W
USB-Ports	5			
Port	USB-A / USB type C			
Maximum power	140 W			
Average operational efficiency	76,5 %			
Efficiency at low load	72,8 %			
Power consumption at no load	0,220 W			
Charging protocol	Power Delivery Profile 3 / PPS / Quick Charge 3.0			
Color	black			
Packaging	cardboard box			
Operating temperature	0 - 25 °C			
Storage temperature	-40 - 80 °C			